















**STEP 1: INSTALL THE HARDWARE**





<p><b>Step 1</b></p>  <p>Remove retainer screw from panel top</p>	<p><b>Step 2</b></p>  <p>Pull back plate off gently</p>	<p><b>Step 3</b></p>  <p>Mount back plate to wall</p>	<p><b>Step 4</b></p>  <p>Hook panel stabilizer strap onto back plate</p>	<p><b>Step 5</b></p>  <p>Connect battery <b>DO NOT DISCONNECT AFTER INSTALLATION</b></p>
<p><b>Step 6</b></p>  <p>Connect wires. DCIN+ to Positive DCIN- to Negative</p>	<p><b>Step 7</b></p>  <p>Connect power supply Positive to + Negative to -</p>	<p><b>Step 8</b></p>  <p>Plug in power supply and secure with screw. Flip bracket upside for decor style plugs.</p>	<p><b>Step 9</b></p>  <p>Tilt panel upward onto back plate until it snaps in place</p>	<p><b>Step 10</b></p>  <p>Replace retainer screw and tighten</p>

**STEP 2: CONNECT WI-FI**






 <p>Settings</p>	 <p>System Settings</p>	 <p>Touch "Wireless Settings"</p>	 <p>Touch "Wi-Fi Settings"</p>	<p>Select the desired network.</p> <p>Enter Wi-Fi password if required.</p>
---	--	--	--	---

*\*Requires Installer code, default is "1111"*

**STEP 3: RUN A CELL TEST**

 <p>Settings</p>	 <p>System Tests</p>	 <p>Cellular Test</p>	 <p>Touch "Start" to begin the test</p>	<p>Cellular radio test started. Please wait... Cellular wireless path tested successfully. Call Central Station to check reports if needed.</p> <p>Successful results will initiate a panel download from the Alarm.com servers, like date, local time, weather, etc., and begins syncing your company's contact info &amp; template settings. Alarm.com account must be created prior to test.</p>
---	---	--	--	---








**STEP 4: CHECK FOR SOFTWARE UPDATES**

 <p>Settings</p>	 <p>Installation</p>	 <p>Upgrade Software</p>	 <p>Touch "Upgrade using Network"</p>	 <p>OK</p>
---	---	---	--	---

*\*NOTE: Download could take up to 3 minutes, depending on your connection speed. After the panel re-starts DO NOT TOUCH THE PANEL for 5 minutes to allow the software to fully install.*

If update is available it will download and install automatically. Once complete, touch "OK" to restart the panel.\*










**STEP 5: PAIR SECURITY & LIFE SAFETY SENSORS**

 <p>Settings</p>	 <p>Installation</p>	 <p>Security Sensors</p>	 <p>AutoLearn Sensor</p>	 <p>"Tamper" Sensor <i>Typically done by opening case, see manual for specifics</i></p>	 <p>The panel will chime and a message will appear. Touch "OK"</p>	 <p>Touch "Add"</p>
---	---	---	---	--	---	--

Select a quick name or custom.

*NOTE: Image Sensors are placed in "pairing mode" by removing and replacing the batteries. See installation manual for details.*

**STEP 6: PAIR Z-WAVE DEVICES**

 <p>Settings</p>	 <p>Installation</p>	 <p>Home Control Devices</p>	 <p>Add Device</p>	 <p>Touch "Pair"</p>	 <p>The panel will begin "looking" for devices</p>
 <p>Press "Learn" button on device</p>	 <p>Device information appears automatically. Edit as desired.</p>	 <p>Touch "Add" to complete the pairing process.</p>	<p><b>NOTE:</b> If the device does not learn in you may need to "Clear Device" first. See installation manual for detailed steps</p>		

**IMPORTANT**

FOR DETAILED INSTRUCTIONS REFER TO THE IQ PANEL INSTALLATION MANUAL ON [DEALERS.GOLSYS.COM](http://DEALERS.GOLSYS.COM)

Security Signaling Residential Fire Alarm and Security Equipment  
ETL Listed  
Conforms to ANSI/UL Standards  
Conforms to ANSI/UL Std. S985, 1023, & 1635  
Certified to ULC Sub. C1023 & ULC Std. S545

Document#: IQPANEL-QG-01-15  
Revision Date: 5/1/15  
Applies to Golsys Part #s:  
QS-9004-VRZ      QS9014-124-00-04  
QS9004-840-00-00      QS9014-484-00-06  
QS9014-840-00-02

    
Intertek  
Golsys Inc. proprietary. Reproduction without permission is not permitted.

ALL IN ONE. ALWAYS CONNECTED



There may be new features available for this IQ Panel.

*After installation is complete follow the instructions inside for connecting to Wi-Fi and performing a software update.*

powered by  **ALARM.COM**



**ONE**  
**CUSTOMER EXPERIENCE**